

SL2045 THRU SL20200


Reverse Voltage - 45 to 200 Volts Forward Current -20.0 Ampere

SURFACE MOUNT SCHOTTKY BARRIER RECTIFIER

Features

- ◆ Schottky Barrier Chip
- ◆ High Thermal Reliability
- ◆ Patented Super Barrier Rectifier Technology
- ◆ High Forward Surge Capability
- ◆ Ultra Low Power Loss, High Efficiency
- ◆ Excellent High Temperature Stability
- ◆ Plastic material-UL flammability 94V-0

TO-277



Mechanical Data

Case : JEDEC TO-277 Molded plastic body

Terminals : Plated Leads Solderable per MIL-STD-202, Method 208

Polarity : Polarity symbol marking on body

Mounting Position: Any

Weight : 0.003 ounce, 0.092 grams

Dimensions in inches and (millimeters)

Maximum Ratings And Electrical Characteristics

Ratings at 25°C ambient temperature unless otherwise specified.

Single phase half-wave 60Hz, resistive or inductive load, for capacitive load current derate by 20%.

Parameter	SYMBOLS	SL 2045	SL 2050	SL 2060	SL 2080	SL 20100	SL 20150	SL 20200	UNIT
Marking Code									
Maximum repetitive peak reverse voltage	V _{RRM}								
Maximum working peak reverse voltage	V _{RWM}	45	50	60	80	100	150	200	V
Maximum DC blocking voltage	V _{DC}								
RMS Reverse voltage	V _{RMS}	32	35	42	56	70	105	140	V
Average Rectified Output Current	I _(O)					20			A
Non-Repetitive Peak Forward Surge 8.3ms Single Half Sine-Wave Superimposed on rated load(JEDEC Method)	I _{FSM}					275			A
Forward Voltage Drop at 20.0A TA=25°C	V _F		0.50	0.55	0.75		0.78		V
Peak reverse current at rated DC blocking voltage	I _R TA=25°C TA=125°C				0.3 15				mA
Typical thermal resistance Junction to Ambient	R _{θJA} R _{θJL}				80 15				°C/W
Operating junction and storage temperature range	T _J , T _{STG}				-55 to +150				°C

Note: 1. Valid Provided that are kept at ambient temperature at a distance of 9.5mm from the case.

2. Fr-4pcb.2oz.Copper, minimum recommend pad layout .18.8mm×14.4mm. Anode pad dimensions 5.6mm×14.4mm.

SL2045 THRU SL20200

Reverse Voltage - 45 to 200 Volts Forward Current -20.0 Ampere

Ratings And Characteristic Curves

Fig.1 - Forward Current Derating Curve




Fig2 : Instantaneous Forward Voltage




Fig3: Surge Forward Current Capability





Fig4: Typical Reverse Characteristics



The curve above is for reference only.